

(No option card)				
Enabled				On
	1	2	3	4

KEY: Off = Open; On = Closed

WARNING: DO NOT CHANGE DIP switches SW 2-5 and SW 2-6: they control the timing of the firing of the hammer and are therefore preset at the factory.

Pinouts:

Pin No.	Symbol	Description	Direction
1	DTR	Data Terminal Ready	Output
2	DSR	Data Set Ready	Input
3	TxD-	Transmit Data-	Output
4	SG	Signal Ground	
5	RxD-	Receive Data-	Input
6	TxD+	Balanced Transmit+	Output
7	NC	No Connection	
8	RxD+	Balanced Receive+	Input
Shield	PG	Protective Ground	

Apple Technical Communications

Keywords: <None>

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 1301